



DINGOL DG184H Three-phase 37.5 KVA AVR

Product description:

DINGOL DG184H THREE PHASE ALTERNATOR 37,5KVA AVR

DINGOL DG184H is a three-phase brushless alternator capable of delivering a maximum power of 37,5KVA complete with AVR voltage regulator.

DINGOL DG184H is equipped with a class H insulation system. All components are subjected to a specific coating and/or impregnation process to safeguard the functionality of the generator and to protect the critical peers in various conditions of use.

The resins and paints used are suitable to make resistant the surface of the static windings, and to give mechanical strength to all rotating components.

DINGOL DG184H is equipped with a fully connected auxiliary buffer winding which contributes to drastically reduce oscillations in parallel, this helps to minimize waveform distortions.

DINGOL DG184H adopt the IP22 (NEMA1) standard for industrial use suitable to guarantee protection from normal weather conditions. For extreme weather conditions, the IP23 standard is also available, which provides protection against water up to 60° from vertical.

The absence of a brush mechanism and the high efficiency of the voltage regulator ensure a low level of interference with radio waves.

DINGOL DG184H is equipped with twelve terminal blocks and are delivered pre-configured in three-phase configuration unless otherwise specified by the customer. However, if it is necessary to change the configuration, a table of possible configurations is shown on the back of the termination box cover.

AVR VOLTAGE REGULATOR



The AVR voltage regulator allows to transfer in a constant way the necessary energy from the excitation stator to the main exciter independently from the power developed instant by instant by the generator.

The high efficiency of the AVR ensures operation even when the residual excitation current is very low. The output current from the excitation rotor that is used to power the main exciter passes through a wave rectifier bridge.

The AVR through sensing regulates the voltage of the output current from the alternator with a margin of control of 0.5% over or under, from no load to full load, including variations from cold to operating temperature, up to cos-phy 0.8 and up to a variation r.p.m. of the motor of 4%.

TECHNICAL CHARACTERISTICS DINGOL DG184H

Phase type: Three-phase
Voltage (V): 400
Frequency (Hz): 50
Revolutions per minute (rpm): 1500
Single-phase power (kVA): ----
Three-phase power (kVA): 40
Alternator type: constant speed
Voltage regulator: AVR
Brushless
Protection degree: IP22 (on request IP 23)
Weight (Kg): 240

Are you looking for an alternator with different characteristics? [Here](#) you can find the whole range DINGOL or other specialized brands.

Pictures and technical data are not binding.

Product features:

Phase: Three phase
Frequency (Hz): 50
Voltage (V): 400
Engine rpm (rpm): 1500
Three-phase power (KW): 30
Three-phase power (KVA): 37.5
Efficiency (%): 86.6
Protection degree: IP22



Shop name

Length (mm): 740

Width (mm): 500

Height (mm): 730

Dry weight (Kg): 230

Brushes: No

PMG: Optional

Type of alternator: Constant Speed

Voltage regulator: AVR



PrestaShop