



SINCRO ET2 LAR Three Phase Synchronous AC Alternator 8.5 kVA AVR

Product description:

Three phase brushes alternator - AVR.

- Self-regulated
- IP23
- Standard voltage 230/400 V - 50 Hz
- Short circuit current greater than 3 In
- Standard coupling IM B35 cone 22.14 / cone 25.4 / cone 35
- Couplings IM B34, IM B35, SAE

The image is purely indicative.

Product features:

Phase: Three phase
Frequency (Hz): 50
Voltage (V): 230 / 400
Engine rpm (rpm): 3000
Poles: 2
Three-phase power (KW): 6.8
Three-phase power (KVA): 8.5
Efficiency (%): 81
Protection degree: IP23
Dry weight (Kg): 34
Brushes: Yes
Type of alternator: Constant Speed
Voltage regulator: AVR

