



## SINCRO FT2 MFR Three Phase Synchronous AC Alternator 16 kVA D-AVR

## **Product description:**

Three phase brushes alternator - DIGITAL AVR.

- Self-regulated
- IP23
- Standard voltage 230/400 V 50 Hz
- Short circuit current greater than 3 In
- Standard coupling IM B35 cone 25.4 / cone 35
- Couplings IM B34, IM B35, SAE
- DIGITAL AVR

The image is purely indicative.

## **Product features:**

Phase: Three phase Frequency (Hz): 50 Voltage (V): 230 / 400 Engine rpm (rpm): 3000

Poles: 2

Three-phase power (KW): 12.8 Three-phase power (KVA): 16

Efficiency (%): 84.5 Protection degree: IP23 Dry weight (Kg): 59

Brushes: Yes

Type of alternator: Constant Speed



Voltage regulator: Digital AVR

