



# CGM 10BET - APERTO CON CENTRALINA MANUALE

## Product description:

## Product features:

Phase: Single phase / Three phase

Maximum power three phase (KW): 8.8

Continuous power three phase (KW): 8

Maximum power three phase (KVA): 11

Continuous power three phase (KVA): 10

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 CEE 5P 400V 16A + 1 CEE 3P 230V 16A

Engine: Briggs&Stratton

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 480

Number cylinders: 2

Oil capacity (L): 1.7

Cooling: Air

Alternator: With brushes

Poles: 2

Fuel tank capacity (L): 8.5

Consumption (L/h): 3.8

Running time (h): 2.3

Acoustic pressure: 73 dB(A) at 7 m

Length (mm): 860

Width (mm): 550

Height (mm): 650



Dry weight (Kg): 115

Silenced: No

Super silenced: No

ATS Switch device : No

Voltage regulator: Compound

Engine manufacturer: Briggs&Stratton