PRAMAC ES8000 THREE PHASE AVR

Product price:

1,923.88 € tax excluded

Product description:

Model with gasoline fuel supply, characterized by a strong structure with tubular frame and adequate protections in sheet steel with oversized tank incorporated.
Designed to satisfy long lasting professional and intensive applications.

HONDA GX series petrol engines

Air cooling
Oil Guard protection
Tear-off starter
Synchronous alternators available with AVR
? Sturdy structure with tubular supporting frame
Sockets on headphones with thermal protection.
? Oversized tanks (11 litres)
? Side protection strips

The image is purely indicative.

Product features:

Phase: Single phase / Three phase
Maximum power single phase (KW): 3.2
Continuous power single phase (KW): 2.96
Maximum power single phase (KVA): 4
Continuous power single phase (KVA): 3.7
Maximum power three phase (KW): 6.6
Continuous power three phase (KW): 5.6
Maximum power three phase (KVA): 8.3
Continuous power three phase (KVA): 7

Fuel: Gasoline
Frequency (Hz): 50
Voltage (V): 230 / 400
Sockets configuration: 1 x 400V 16A 3P+N+T CEE IP44 - 1 x 230V 16A SCHUKO IP54 - 1 x 230V 16A 2P+T CEE IP44
Engine: Honda GX390 Recoil, naturally aspirated
Engine rpm (rpm): 3000
Speed governor: Mechanical
Ignition: Recoil
Starting system: Pull starter
Engine capacity (cm^3): 389
Oil capacity (L): 1.1
Cooling: Air
Alternator: With brushes
Poles: 2
Fuel tank capacity (L): 11
Consumption (L/h): 2.1 at 75% of the load / 2.9 at 100% of the load
Running time (h): 5.1 at 75% of the load / 3.8 at 100% of the load
Acoustic power: 97 dB(A)
Acoustic pressure: 69 dB(A) at 7 m
Length (mm): 729
Width (mm): 500
Height (mm): 536
Dry weight (Kg): 81
Silenced: No
Super silenced: No
Product type: Generator
ATS Switch device : No
Voltage regulator: AVR
Engine manufacturer: Honda