



# PRAMAC GSW30P COFANATO CON QUADRO COMANDO MANUALE

## Product description:

## Product features:

Phase: Three phase

Maximum power three phase (KW): 26

Continuous power three phase (KW): 24.4

Maximum power three phase (KVA): 32.5

Continuous power three phase (KVA): 30.5

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 400

Sockets configuration: 1 x 400V 63A 3P+N+T - 1 x 400V 32A 3P+N+T CEE - 2 x 230V 16A 2P+T CEE - 1 x 230V 16A SCHUKO

Engine: PERKINS 1103A-33G, naturally aspirated

Speed governor: Mechanical

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 3300

Number cylinders: 3

Cylinders' position: In line

Oil capacity (L): 8.3

Cooling: Water

Alternator: Mecc Alte ECP28-VL/4, brushless

Poles: 4

Fuel tank capacity (L): 68

Consumption (L/h): 5.4 at 75% of the load / 7.1 at 100% of the load

Running time (h): 12.6 at 75% of the load / 9.6 at 100% of the load

Acoustic power: 93 dB(A)



Shop name

---

Acoustic pressure: 64 dB(A) at 7 m  
Length (mm): 2000  
Width (mm): 920  
Height (mm): 1310  
Dry weight (Kg): 877  
Silenced: Yes  
Super silenced: Yes  
Product type: Generator  
ATS Switch device : No  
Voltage regulator: AVR  
Engine manufacturer: Perkins



---

PrestaShop