

Generator set Nanni QMS16M

16.2 kW max at 1500 rpm

Engine base

- 4 strokes Diesel engine tested in all marine or industrial applications throughout the world.
- Engine block in cast iron type tunnel and timing gear.

Injection and combustion system

- The Super Glow System comes as standard equipment to start the engine in cold temperatures.
- The E-TVCS injection system produces an ideal air/fuel mixture by creating three vortexes in the combustion chamber. The combustion efficiency is improved, resulting in low fuel consumption.

Frequency

(Hz)

50

Single-phased output with power factor $\cos phi = 1$ *Continuous (COP) and max (PRP) power rating according to ISO 8528-1

Cooling system

- Cooling is ensured by heat exchange between coolant and seawater in an heat exchanger, or via a Keel Cooling system.
- Seawater pump with rubber impeller.

Power * (kW)

max

16.2

cont.

13.9

Generator

Amperes (A)

cont.

60.4

max

70.4

- Delivering a continuous power of 13.9 kW and able to provide up to 16.2 kW.
- IP21 protection (additional level available on demand).

Engine main features

- Kubota base Diesel engine
- 4 cylinders in line
- · Closed cooling with heat exchanger
- Engine block in cast iron

Generator main features

- · Class H insulation
- 50 Hz
- Voltage accuracy of ± 1.5%
- Radio interference suppression
- Electronic regulator

Standard equipment

- Extension delivered by meter
- · Closed cooling with heat exchanger
- Wet exhaust
- 12V Single-pole electrical system
- Safety shutdowns on low oil pressure and high coolant temperature
- Eco GE panel
- Rubber mounts
- Oil drain pump mounted on the engine

Weight and dimensions

Generator set ratings

Voltage

(V)

230

Dry weight (kg)	328
Length (mm)	1014
Width (mm)	548
Height (mm)	691

Optional equipment

- Seawater hoses
- Seawater filter
- Siphon breaker
- Fuel feed system piping
- Exhaust system
- Fuel prefilter
- Keel Cooling
- Vertical dry exhaust
- 12V Double-pole electrical system
- Luxe GE panel (instead of Eco GE panel)
- Additional electric fuel feed pump



Generator set QMS16M

Engine specifications

Engine base Kubota

Cycle 4 strokes Diesel

Number of cylinders 4 in line
Displacement (cm³) 2197
Bore and stroke (mm) 87 x 92,4

Combustion system Indirect (E-TVCS)

Rated rpm 1500 Intake Natural

Fuel system

Fuel injection pressure (bar) 140

Fuel injection pump In line, Type Bosch MD mini

Fuel feed pump Mechanical

Governor type All speed mechanical

Cooling system

Seawater pump Neoprene rotor

Coolant pump type Coaxial alternator driven

Coolant capacity (I) 7.5

Exhaust manifold Fresh water cooled Exhaust elbow. Water injected

Max allowable back pressure (bar) 0.127 Max exhaust gas temperature (°C) 550

Lubrication system

Oil pan capacity (I) 7.5

Oil type API-CF mini 15W40
Oil filter Full flow type filter
Lubrication system Forced by trochoid pump

Engine Electrical System

Engine alternator (V-A) 12 - 40

Battery recommended (Ah) 120

Starter motor (V-kW) 12 - 1.4

Fuel consumption

Fuel consumption at full load (I/h) 4.8

Air requirements

Combustion air at 25°C (m³/h) 90 Flow for the evacuation of radiant heat (m³/h) 430

near (iii /ii)

Installation data

Exhaust connexion (mm) 50
Fuel connexion (mm) 8

Fuel pump - Max suction height (m) 0.5 (Standard pump)

1.8 (with add. electrical pump)

Sea Water pump connexion (mm) 32

Engine Operating Angle 15° continuous (30° maxi)

Instrument panel

Eco GE






- · Start and stop buttons
- · Low oil pressure warning light
- · Coolant temperature warning light
- · Preheat warning light
- · Battery charge warning light
- · Oil pressure indicator
- · Coolant temperature indicator *

*Only on Luxe GE panel

Main components



- 1. Oil drain pump
- 2. Fuel feed pump
- 3. Fuel filter
- 4. Expansion tank
- 5. Seawater pump
- 6. Oil filter
- 7. Oil filler port
- 8. Exhaust elbow.

Your dealer

Certified

ISO 9001

BUREAU VERITAS

Certification