

# Generator set Nanni QMS7.5M



## 7.5 kW max at 1500 rpm

## **Engine base**

- 4 strokes Diesel engine tested in all marine or industrial applications throughout the world.
- Engine block in cast iron type tunnel and timing gear.

#### Injection and combustion system

- The Super Glow System comes as standard equipment to start the engine in cold temperatures.
- The E-TVCS injection system produces an ideal air/fuel mixture by creating three vortexes in the combustion chamber. The combustion efficiency is improved, resulting in low fuel consumption.

### **Generator set ratings**

Voltage	Frequency	Amperes (A)		Frequency Amperes (		Powe	er * (kW)
(V)	(Hz)	max	cont.	max	cont.		
230	50	32.6	28.7	7.5	6.6		

Single-phased output with power factor cos phi = 1 \*Continuous (COP) and max (PRP) power rating according to ISO 8528-1

#### Weight and dimensions

	Without sound shield	With sound shield
Dry weight (kg)	224	271
Length (mm)	840	950
Width (mm)	489	540
Height (mm)	620	715

### **Cooling system**

- Cooling is ensured by heat exchange between coolant and seawater in an heat exchanger, or via a Keel Cooling system.
- Seawater pump with rubber impeller.

## Generator

- Delivering a continuous power of 6.6 kW and able to provide up to 7.5 kW.
- IP21 protection (additional level available on demand).

#### Sound shield

• Available as an option. Connexions to the fuel, cooling and electrical circuit in front of the sound enclosure.

#### **Engine main features**

- Kubota base Diesel engine
- 3 cylinders in line
- · Closed cooling with heat exchanger
- Engine block in cast iron

#### **Generator main features**

- Class H insulation
- 50 Hz
- Voltage accuracy of ± 1.5%
- Radio interference suppression
- Electronic regulator

#### **Standard equipment**

- Extension delivered by meter
- · Closed cooling with heat exchanger
- Wet exhaust
- 12V Single-pole electrical system
- Safety shutdowns on low oil pressure and high coolant temperature
- Eco GE panel 1
- Rubber mounts
- Oil drain pump mounted on the engine <sup>1</sup>

#### **Optional equipment**

- Sound shield
- Seawater hoses
- Seawater filter
- Siphon breaker
- Fuel feed system piping
- Exhaust system
- Fuel prefilter
- Keel Cooling<sup>2</sup>
- Vertical dry exhaust <sup>2</sup>
- 12V Double-pole electrical system <sup>2</sup>
- Eco GE or Luxe GE instrument panel
- Additional electric fuel feed pump

<sup>1</sup> Optional in version with sound enclosure <sup>2</sup> Not available in version with sound enclosure



www.nannidiesel.com

## **Generator set QMS7.5M**

## **Engine specifications**

Engine base
Cycle
Number of cylinders
Displacement (cm <sup>3</sup> )
Bore and stroke (mm)
Combustion system
Rated rpm
Intake

4 strokes Diesel 3 in line 1123 78 x 78.4 Indirect (E-TVCS) 1500 Natural

Kubota

## **Fuel system**

Fuel injection pressure (bar)	140
Fuel injection pump	In line, Type Bosch MD mini
Fuel feed pump	Mechanical
Governor type	All speed mechanical

## **Cooling system**

Seawater pump	Neoprene rotor
Coolant pump type	Coaxial alternator driven
Coolant capacity (I)	5
Exhaust manifold	Fresh water cooled
Exhaust elbow.	Water injected
Max allowable back pressure (bar)	0.127
Max exhaust gas temperature (°C)	550

#### Lubrication system

Oil pan capacity (I)	5.1
Oil type	API-CF mini 15W40
Oil filter	Full flow type filter
Lubrication system	Forced by trochoid pump

## **Engine Electrical System**

Engine alternator (V-A)	12 - 40
Battery recommended (Ah)	75
Starter motor (V-kW)	12 - 1

## **Fuel consumption**

Fuel consumption at full load (I/h)	2.5
r der consumption at run road (mit)	2.0

### Air requirements

Combustion air at 25°C (m <sup>3</sup> /h)	50
Flow for the evacuation of radiant heat (m <sup>3</sup> /h)	206

## Installation data

Exhaust connexion (mm)	50	
Fuel connexion (mm)	8	
First many and such that the first day	0.5 (Standard pump)	
Fuel pump - Max suction height (m)	1.8 (with add. electrical pump)	
Sea Water pump connexion (mm)	25	
Engine Operating Angle	15° continuous (30° maxi)	

## Instrument panel

#### Eco GE






- · Start and stop buttons
- · Low oil pressure warning light
- · Coolant temperature warning light
- · Preheat warning light
- · Battery charge warning light
- · Oil pressure indicator \*
- · Coolant temperature indicator \*

\*Only on Luxe GE panel


#### Main components



- 1. Oil drain pump\*\*
- 2. Fuel feed pump
- 3. Fuel filter
- 4. Expansion tank

\*\*Optional in version with sound enclosure (supplied loose

#### Sound enclosure (optional)



- 7. Oil filler port 8. Exhaust elbow.

6. Oil filter

- 1. Start and Stop buttons
- 2. Warning displays
- 3. Hourmeter
- 4. Emergency Stop
- 5. Circuit breaker
- 6. Exhaust outlet
- 7. Seawater connection
- 8. Fuel connection
- 9. Connection for additional panel
- 10. Power cables connection
- 11. Battery connections



