



LINZ E1C13M D/2 Single-phase alternator 115/230V 15 kVA 50 Hz Brushless

Reference: E1C13M D/2 50 Hz 60 Hz

The E1C13M series consists of single-phase, brushless, 2-pole alternators with auxiliary winding (charged on the condenser) that ensures voltage regulation.

CHARACTERISTICS

- Compact and easy to assemble
- Possibility of feeding any type of load
- Wide range of accessories
- High efficiency
- Gamma: Single-phase alternators
- Poles: 2
- Phases: Single-phase
- Adjustment: CONDENSER
- Application: FLOW-UP
- Images and technical data are not binding.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	15
Maximum power single phase (KVA)	15
Frequency (Hz)	50 / 60
Voltage (V)	115 / 230
Engine rpm (rpm)	3000
Alternator	Synchronous, brushless
Poles	2
Single-phase power (KVA)	15
Protection degree	IP21
Motor insulation class	H

Length (mm)	495
Width (mm)	270
Height (mm)	375
Brushes	No
Type of alternator	Constant Speed
Voltage regulator	Capacitor
Weight (Kg)	77.7
