



ENDRESS ESE 206 HS-GT Synchronous 2.9 kVA petrol generator

Reference: 112300

Synchronous current generator with a compact 163 cc. Honda petrol engine, tear-off starter and a large 20 litre tank, which guarantees an autonomy of 22 hours!

ENDRESS ESE 206 HS-GT is equipped with an automatic stop system in case of lack of oil, overload protection, AVR.

Suitable for supplying energy to :

- Power tools up to 2100 W
- Gardening tools up to 1500 W
- Compressors or pumps up to 1100 W

Manelservice delivers free ENDRESS ESE 206 HS-GT throughout Italy.

Images and technical data are not binding.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	2.5
Continuous power single phase (KW)	2.2
Maximum power single phase (KVA)	2.9
Continuous power single phase (KVA)	2.6
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	2 x 230V 16A CE
Engine	Honda GX160
Engine rpm (rpm)	3000
Ignition	Recoil
Starting system	Manual
Engine capacity (cm ³)	163

Alternator	Synchronous
Poles	2
Nominal current (A)	10.9
Fuel tank capacity (L)	20
Consumption (L/h)	0.9
Running time (h)	22
Acoustic power	96 dB(A)
Acoustic pressure	71 dB(A) at 7 m
Length (mm)	637
Width (mm)	473
Height (mm)	500
Dry weight (Kg)	41
Silenced	No
Super silenced	No
Voltage regulator	AVR
Engine manufacturer	Honda