



ENDRESS ESE 2000i Generator Inverter petrol 2 kVA

Reference: 110005

Portable current generator with inverter inverter technology for low consumption.
 The ENDRESS ESE 2000i is equipped with an automatic stop system in the event of a lack of oil and overload protection.

Images and technical data are not binding.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	2
Continuous power single phase (KW)	1.6
Maximum power single phase (KVA)	2
Continuous power single phase (KVA)	1.6
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x 230V - 1 x 12V
Engine rpm (rpm)	3000
Ignition	Recoil
Starting system	Manual
Poles	2
Fuel tank capacity (L)	4
Consumption (L/h)	0.7 at 75% of the load
Running time (h)	6 at 75% of the load
Acoustic pressure	51 dB(A) at 7 m
Length (mm)	540

Width (mm)	330
Height (mm)	505
Dry weight (Kg)	20
Silenced	Yes
Super silenced	Yes
Voltage regulator	Inverter
Engine manufacturer	Honda
