



## LINZ E1E10L L Single-phase alternator 110V/220V 9.75 kVA 60 Hz AVR

Reference: E1E10L L 60 Hz

The **SPE** and **E1E** series consist of single-phase 2-pole alternators with brushes and AVR electronic regulation.

### CHARACTERISTICS

- Compact and easy to assemble
- High voltage accuracy
- Wide range of accessories
- AVR with built-in protections
- Range: Single-phase alternators
- Poles: 2
- Phases: Single-phase
- Adjustment: AVR
- Application: PORTABLE

Images and technical data are not binding.

### Technical Sheet

Phase	Single phase
Continuous power single phase (KW)	9.75
Continuous power single phase (KVA)	9.75
Frequency (Hz)	60
Voltage (V)	110 / 220
Engine rpm (rpm)	3600
Alternator	Synchronous, brushless
Poles	2
Single-phase power (KVA)	8.4
Protection degree	IP21
Motor insulation class	H

---

Length (mm)	395
Width (mm)	195
Height (mm)	297
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	37.5

---