



LINZ E1E11M B Single-phase alternator 115V/230V 10 kVA 50 Hz AVR

Reference: E1E11M B 50 Hz B3/B14

The **SPE** and **E1E** series consist of single-phase, 2-pole alternators with brushes and electronic AVR regulation.

FEATURES

- Compact and easy to assemble
- High voltage accuracy
- Wide range of accessories
- AVR with built-in protections
- Range: Single-phase alternators
- Poles: 2
- Phases: Single-phase
- Regulation: AVR
- Application: PORTABLE
- Available in 50 Hz and 60 Hz versions

Technical Sheet

Phase	Single phase
Continuous power single phase (KW)	10
Continuous power single phase (KVA)	10
Frequency (Hz)	50 / 60
Voltage (V)	115 / 230
Engine rpm (rpm)	3000
Alternator	Synchronous, brushless
Poles	2
Single-phase power (KVA)	10
Protection degree	IP21
Motor insulation class	H
Length (mm)	415

Width (mm)	230
Height (mm)	215
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	48
