



LINZ E1E13M D Single-phase alternator 115V/230V 15 kVA 50 Hz AVR

Reference: E1E13M D 50 Hz J609b

The **SPE** and **E1E** series consist of single-phase 2-pole alternators with brushes and AVR electronic regulation.

CHARACTERISTICS

- Compact and easy to assemble
 - High voltage accuracy
 - Wide range of accessories
 - AVR with built-in protections
 - Range: Single-phase alternators
 - Poles: 2
 - Phases: Single-phase
 - Adjustment: AVR
 - Application: PORTABLE
- Product available in 50 Hz and 60 Hz versions

Images and technical data are not binding.

Technical Sheet

Phase	Single phase
Continuous power single phase (KW)	15
Continuous power single phase (KVA)	15
Frequency (Hz)	50 / 60
Voltage (V)	115 / 230
Engine rpm (rpm)	3000
Alternator	Synchronous, brushless
Poles	2
Single-phase power (KVA)	15
Protection degree	IP21
Motor insulation class	H

Length (mm)	495
Width (mm)	270
Height (mm)	379
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	77.7
