



## LINZ SLS18 MD Single-phase alternator 15 kVA 50 Hz with AVR

Reference: SLS18 MD 50 Hz

The alternators of the SLS series are single-phase 4-pole, brushless, equipped with electronic regulator (AVR).

### CHARACTERISTICS

- Compact and mechanically resistant
- Excellent wave form
- Minimum maintenance
- High efficiency
- Type: Single-phase alternators
- Poles: 4
- Phases: Single-phase
- Regulation: AVR
- Application: INDUSTRIAL, TELECOMMUNICATION

### Technical Sheet

Phase	Single phase
Continuous power single phase (KW)	15
Continuous power single phase (KVA)	15
Frequency (Hz)	50
Voltage (V)	220 / 230 / 240
Engine rpm (rpm)	1500
Alternator	Synchronous, brushless
Poles	4
Single-phase power (KVA)	15
Protection degree	IP23
Motor insulation class	H

---

Length (mm)	370
Width (mm)	450
Height (mm)	450
Brushes	No
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	115

---