



LINZ E1S13M D/2 Three-phase alternator 230V/400V 22 kVA 50 Hz 60 Hz Compound

Reference: E1S13M D/2 50 Hz J609 c25.4

E1S/2 series are three-phase 2 poles alternators with brushes and compound regulation..

CHARACTERISTICS

- Possibility to feed any type of load
- Compact and easy to assemble
- High starting capacity
- High efficiency

- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: COMPOUND
- Application: PORTABLE
product available in 50 Hz and 60 Hz versions

Technical Sheet

Phase	Three phase
Continuous power three phase (KW)	17.6
Continuous power three phase (KVA)	22
Frequency (Hz)	50 / 60
Voltage (V)	230 / 400
Engine rpm (rpm)	3000
Alternator	Synchronous
Poles	2
Three-phase power (KVA)	22
Protection degree	IP21

Motor insulation class	H
Length (mm)	495
Width (mm)	270
Height (mm)	379
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	Compound
Weight (Kg)	77.7