



## LINZ SLT18 MD Three-phase alternator 4 poles 20 kVA 50 Hz AVR

Reference: SLT18 MD 50 Hz

The alternators of **SLT18** series are three-phase 4 poles brushless with electronic regulation (AVR) with single-phase sensing.

### CHARACTERISTICS

- Compact and mechanically resistant
- Excellent wave form
- Minimum maintenance
- High efficiency
- 
- Type: Three-phase alternators
- Poles: 4
- Phases: Three-phase
- Regulation: AVR
- Application: INDUSTRIAL, TELECOMMUNICATION

### Technical Sheet

Phase	Three phase
Continuous power three phase (KW)	16
Continuous power three phase (KVA)	20
Frequency (Hz)	50
Voltage (V)	230 / 400
Engine rpm (rpm)	1500

Alternator	Synchronous
Poles	4
Three-phase power (KVA)	20
Protection degree	IP23
Motor insulation class	H
Length (mm)	370
Width (mm)	362
Height (mm)	439
Brushes	No
Type of alternator	Constant Speed
Voltage regulator	AVR
Weight (Kg)	116