



GENSET MG 132 S-I - SINGLE-PHASE/THREE-PHASE GENERATOR 132 KVA AVR

Reference: MG 132 S-I

GENSET MG 132 S-I

The GENSET MG 132 S-I is a 88 KVA single/three phase diesel generator set with electric start and AVR voltage regulator. The GENSET MG 132 S-I also has a low fuel consumption: only 21.6 Lt/h at 75% of the load. Thanks to the high quality and efficiency of its components, the GENSET MG 132 S-I generator set is ideal for various types of professional work such as on large construction sites.

Images and technical data are not binding.

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	35.2
Maximum power single phase (KVA)	44
Maximum power three phase (KW)	105.6
Continuous power three phase (KW)	96
Maximum power three phase (KVA)	132
Continuous power three phase (KVA)	120
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	Terminal box
Engine	FPT (IVECO) NEF45TM3 turbo
Emissions Regulations	Stationary Use
Engine rpm (rpm)	1500
Starting system	Electric
Engine capacity (cm ³)	4500
Number cylinders	4

Cooling	Water
Alternator	Synchronous
Protection degree	IP23
Motor insulation class	H
Fuel tank capacity (L)	230
Consumption (L/h)	21.6
Running time (h)	10.65
Acoustic power	95 dB(A)
Acoustic pressure	70 dB(A) at 7 m
Length (mm)	2900
Width (mm)	1100
Height (mm)	1800
Dry weight (Kg)	1630
Silenced	Yes
Super silenced	Yes
Product type	Generator
ATS Switch device	ATS Included
Voltage regulator	AVR
Engine manufacturer	FPT Iveco