



## BRIGGS AND STRATTON P3000

Reference: 030674

Get more power for large open spaces with inverter technology, which is quieter than traditional camping generators.

### PowerSmart™ Series Technology

Inverter technology produces a silent and constant power supply for motorhomes, small businesses or even home backup.

### Silent and efficient power

Silent inverter technology offers stable and uniform power security for sensitive electronic components. Its engine speed adjusts automatically, further reducing noise, fuel consumption and emissions.

### Fuel level indicator

Conveniently displays the amount of fuel remaining.

### Parallel connection kit

Allows you to connect two units for even more power, ideal for motorhomes with air conditioners. The parallel connection kit is sold separately.

### Multiple outputs for your power needs

2 x 230V Household sockets, 12V DC charging output, USB 5V port

### LCD Statstation™ Display

The easy-to-read LCD screen shows the amount of energy used, total unit hours and maintenance reminders, including oil, air filter and spark plug changes.

### Easy mobility

The unique double handle design and the luggage style telescopic handle make mobility child's play.

Not binding images and technical data.

## Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	3
Continuous power single phase (KW)	2.6
Maximum power single phase (KVA)	3.75
Continuous power single phase (KVA)	3.25

Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	2 x 230V 16A
Engine	Briggs&Stratton
Engine rpm (rpm)	3000
Starting system	Manual
Engine capacity (cm <sup>3</sup> )	171
Number cylinders	1
Fuel tank capacity (L)	5.6
Consumption (L/h)	0.56
Running time (h)	10
Length (mm)	660
Width (mm)	350
Height (mm)	530
Dry weight (Kg)	38
Silenced	Yes
Super silenced	Yes
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	Inverter
Engine manufacturer	Briggs&Stratton