



CGM D4000 SINGLE PHASE GENERATOR 4KVA

Reference: CGM D4000

CGM D4000 single-phase 4 KVA generating set

CGM D4000 single-phase 4 KVA generator set with Kohler engine powered by STAGE V diesel at 3000 rpm, compact and easy to use, mounted on a fixed base with rubber vibration dampers.

The CGM D4000 generator set consists of a Made in Italy alternator from Linz or NSM, self-excited without brushes and with optional capacitor or **AVR** voltage regulator. The CGM D4000 generator set is equipped with electric start with 12V battery and with a low fuel consumption, in fact it consumes only 1 liter/hour at 75% of the load. This CGM D4000 is perfect for outdoor use such as for hobby use.

The CGM D4000 generator set is part of the CLASSIC DIESEL series and are characterized by lower consumption and a longer life expectancy than the gasoline-powered range. The CGM D4000 generating set at 3000 rpm is suitable for emergency use only. It is not recommended for use for more than 6 hours continuously and for more than 500 hours per year.

Technical characteristics of CGM D4000:

Phase type: Single phase
Maximum power: 3.9 KW
Continuous power: 3.6 KW
Maximum power: 4.4 KVA
Continuous power: 4 KVA
Fuel: Diesel
Voltage: 230 V
Frequency: 50 Hz
Motor: KOHLER KD15-350
Engine speed: 3000 rpm
Starting: Electric
Voltage regulator system: AVR
Consumption: 1 Lt/h at 75% of the load
Tank capacity: 4.3 Lt
Autonomy: 4.3 h at 75% load
Length: 780 mm
Width: 510 mm
Height: 500 mm
Weight: 80 Kg

Discover the full range reserved for [terrestrial generator sets](#) of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	3.9
Continuous power single phase (KW)	3.6
Maximum power single phase (KVA)	4.4
Continuous power single phase (KVA)	4
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x 230V 16A 3P CEE - 1 x 230V SCHUKO
Engine	Kohler KD 15-350
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Electric
Engine capacity (cm ³)	349
Number cylinders	1
Alternator	Made in Italy
Poles	2
Fuel tank capacity (L)	4.3
Consumption (L/h)	1
Running time (h)	4.3
Length (mm)	780
Width (mm)	510
Height (mm)	500
Dry weight (Kg)	80
Silenced	No
Super silenced	No
Product type	Generator

ATS Switch device	Optional ATS
Voltage regulator	AVR
Engine manufacturer	Kohler
