



## HELVI PROGRESS 35B

Reference: 99000040

### HELVI PROGRESS35B Battery charger

HELVI PROGRESS35B is a professional battery charger for large charging stations equipped with voltage and current selector, ammeter, voltmeter and automatic thermal protection.

HELVI PROGRESS35B is perfect for charging batteries with a voltage of 6 V, 12 V, 24 V, 36 V or 48 V and a charging current of 25 A. The HELVI PROGRESS35B battery charger can charge batteries for various types of vehicles such as motorbikes, cars, vans, boats and tractors. The main applications of the HELVI PROGRESS35B battery charger are in the automotive, domestic, agricultural and building construction sectors. HELVI PROGRESS35B is ideal for batteries with various types of voltage from 6 V to 48 V for large charging stations.

HELVI PROGRESS35B is a single-phase battery charger with 230 V power supply and 50/60 Hz frequency. HELVI PROGRESS35B has a nominal power of 1830 W for a maximum current of 38 A.

The nominal charging capacity of the HELVI PROGRESS35B battery charger is 375 Ah and has 6 charging positions. HELVI PROGRESS35B is very compact and light thanks to its weight of about 22 Kg equipped with a carrying handle.

#### Technical characteristics of the HELVI PROGRESS35B battery charger:

Phase type: Single-phase  
Voltage: 230 V  
Frequency: 50/60 Hz  
Power: 1830 W  
Battery voltage: 6/12/24/36/48 V  
Maximum current: 38 A  
Charging current: 25 A  
Charging capacity: 375 Ah 15h  
Charging positions: 12  
Length: 245 mm  
Width: 250 mm  
Height: 435 mm  
Weight: 22.2 Kg

If you are looking for another product similar to the HELVI PROGRESS35B portable charger, then we recommend that you take a look at the entire range dedicated to battery chargers.

Images and technical data are not binding.

#### Technical Sheet

|                |              |
|----------------|--------------|
| Phase          | Single phase |
| Frequency (Hz) | 50 / 60      |

|                      |                       |
|----------------------|-----------------------|
| Voltage (V)          | 230                   |
| Power (W)            | 1830                  |
| Adjustment positions | 12                    |
| Nominal current (A)  | 25                    |
| Charge capacity (Ah) | 375                   |
| Battery voltage (V)  | 6 / 12 / 24 / 36 / 48 |
| Charging voltage (V) | 6 / 12 / 24 / 36 / 48 |
| Current max (A)      | 38                    |
| Length (mm)          | 245                   |
| Width (mm)           | 250                   |
| Height (mm)          | 435                   |
| Product type         | Battery Charger       |
| Weight (Kg)          | 22.2                  |