



## HONDA EU 20i Petrol Inverter Generator 2 kW 2.5 kVA

Reference: EU20IT1 /

### Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	2
Continuous power single phase (KW)	1.6
Maximum power single phase (KVA)	2.5
Continuous power single phase (KVA)	2
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	2 x 230V SCHUKO
Engine	Honda GX100, 4 stroke, OHV
Engine rpm (rpm)	5000
Ignition	Transistorized
Starting system	Recoil
Engine capacity (cm <sup>3</sup> )	98.5
Number cylinders	1
Oil capacity (L)	0.4
Cooling	Forced air
Alternator	Multipolar
Bore x stroke (mm)	56 x 40
Fuel tank capacity (L)	3.6
Consumption (L/h)	0.93

Running time (h)	3.83
Acoustic power	89 dB(A)
Acoustic pressure	71 dB(A)
Length (mm)	512
Width (mm)	290
Height (mm)	425
Dry weight (Kg)	20.7
Inverter	Yes
AVR	No
Compound	No
Silenced	Yes
Super silenced	Yes
Link Noleggio	<a href="https://www.manelservice.com/eu-20i-2-5-kva/#noleggio">https://www.manelservice.com/eu-20i-2-5-kva/#noleggio</a>