



## GENMAC Click RG4000KO GENERATOR 4,1KVA

Reference:

### GENMAC Click RG4000KO SINGLE-PHASE GENERATOR 4,1KVA

The generator Genmac Click RG4000KO single-phase is equipped with a Kohler diesel powered engine capable of delivering 4,1KVA with capacitor voltage regulator (AVR optional).

**High quality** Professional Diesel Generators, **Genmac Click Diesel** series with power of **4,1KVA**, are equipped with **Kohler oversized engine** with air-cooled to 3000 RPM.

Professional Genmac Click **diesel generators**, are highly reliable **machines**, built with **quality components** to be **used in professional field**, where reliability is fundamental.

The KOHLER engine is oversized compared to generators of equal power normally available on the market.

This feature is essential to ensure high reliability of the generator, reduce the effort and increase **the life span by lowering the noise level**.

All KOHLER motors **are built using the best materials, the most innovative technics and the most advanced quality control methods**.

Each engine is carefully tested in order to prove its perfect operation before delivery.

In case of need, however, **KOHLER's service is always at your disposal**.

The 4,1KVA generator is equipped with capacitor voltage regulator, on request it can be supplied with AVR.

### AVR Voltage Regulator

All models in the Genmac Combipro series are available with optional AVR voltage regulator. The AVR is a device that allows to **maintain the output more constant and less load-dependent**. Thanks to this card you have fewer drops or current peaks and this makes it safer to use the various devices connected, improving their performance and durability.

**The model equipped with AVR card is highly recommended**, as it guarantees a significant improvement in the stability of the output; this feature makes the generators particularly suitable with common use machines with reactive load such as refrigerators, freezers, air conditioners and garden machines. Thanks to the AVR you can enjoy greater stability and thus increase the life of your devices.

### TECHNICAL FEATURES OF GENERATOR GENMAC CLICK RG4000KO 4,1KVA

Voltage regulator : capacitor (AVR Optional)

Power supply: Diesel

Starting: Manual

Phase type: Single phase

Continuous power: 3.9KVA / 3.5KW  
 Maximum power: 4.1KVA / 3.7KW  
 Motor: KOHLER KD350  
 Socket panel: 2 x schuko 16A 230V  
 Voltage: 230V  
 Frequency: 50 Hz  
 3000 rpm  
 Tank: 5 Lt.  
 Autonomy @ 75%: 4,5 h fixed rpm  
 Starting: Manual  
 Length (mm): 740  
 Width (mm): 540  
 Height (mm): 600  
 Dry weight (Kg): 82

If you are looking for another product then you can see on [our catalog other](#).

Images and technical data are not binding.

## Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	3.7
Continuous power single phase (KW)	3.5
Maximum power single phase (KVA)	4.1
Continuous power single phase (KVA)	3.9
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	230
Engine	Kohler KD 350
Engine rpm (rpm)	3000
Starting system	Manuale
Cooling	Air
Poles	2
Fuel tank capacity (L)	5
Running time (h)	15
Length (mm)	740
Width (mm)	540
Height (mm)	600
Dry weight (Kg)	82
ATS Switch device	No ATS
Voltage regulator	AVR (optional)

---

Engine manufacturer

Kohler

---