



## SINCRO IB4 SB SINGLE-THREE PHASE ALTERNATOR 30KVA AVR

Reference: IB4 SB

Three phase brushless alternator - AVR.

- Insulation class H
- IP23
- Standard voltage 230/400 V - 50 Hz
- Leads 12
- Bearings: Bearings are dimensioned for heavy duty
- Transient features: Transient voltage drop for rated step load at 0.8 power factor is less than 18%
- Single-phase operation: IB4 alternators can be connected for single-phase use

The image is purely indicative.

### Technical Sheet

Phase	Single phase / Three phase
Frequency (Hz)	50
Voltage (V)	230 / 400
Engine rpm (rpm)	1500
Poles	4
Single-phase power (KW)	14.4
Single-phase power (KVA)	18
Three-phase power (KW)	24
Three-phase power (KVA)	30
Efficiency (%)	88.2
Protection degree	IP23
Dry weight (Kg)	129
Brushes	No
Type of alternator	Constant Speed
Voltage regulator	AVR