



GREEN POWER GP 8000XM/HE SINGLE PHASE GENERATOR STAGE V ELECTRIC START 6,6KVA

Reference: 00017X

GREEN POWER GP 8000XM/HE SINGLE-PHASE GENERATOR STAGEV ELECTRIC START 6,6KVA

The generator GREENPOWER GP 8000XM/HE single-phase is equipped with a gasoline-powered HONDA GX390 **StageV** engine, and is complete with capacitor voltage regulator (**AVR optional**).

GREENPOWER GP 8000XM/HE features electric start and has low fuel consumption, in fact it consumes only 2.1 liters/hour at 75% load for up to 2.9 hours of operation. Extremely practical sockets and controls make starting and operating the generator easy and quick.

The generator is compact and convenient to maneuver and transport thanks to its compact size, its weight of 94 kg as well as the practical tubular handles. In addition, it is equipped with a practical and convenient electric start system, so that it can be put into operation quickly and easily.

The GREENPOWER GP 8000XM/HE generator is equipped with a high performance HONDA GX390 StageV engine which allows this machine to deliver a maximum single-phase power of 6.6KVA.

The voltage regulator is an electronic device capable of automatically adjusting the voltage and possibly the frequency and/or the current according to set values. These values can be modified or bound to the technical characteristics of the regulator itself.

In essence, thanks to this device, the alternating current coming from the alternator is regulated and transformed into direct current at constant voltage.

STAGEV EMISSIONS REGULATION

The STAGEV standard defines the guidelines and limits for engine gas emissions. The regulation is respected through the installation of special anti-particulate filters in the gensets, but an indispensable condition for the filter to function correctly is that the genset works at its design temperature.

The control panel of the GREENPOWER GP 8000XM/HE generator is composed of:

- Output sockets: 1x 230V 32A CEE / 1x 230V 16A SCHUKO
- Thermal circuit breaker
- Voltmeter

TECHNICAL FEATURES GREENPOWER GP 8000XM/HE

Phase Type: Single Phase
Continuous Use Power: 6 KVA / 6 KW

Maximum Power: 6.6 KVA / 6.6 KW
Motor: HONDA GX390
Motor RPM: 3000 rpm
Emission Standard: StageV
Start: Electric
Fuel: Gasoline
Voltage: 230 V
Frequency: 50 Hz
Socket panel: 1 x Schuko 16A 230V / 1 x CEE 32A 230V
Tank capacity: 6.1l
Autonomy at 75% load: 2.9 h
Consumption at 75% load: 2.1 Lt/h
Length: 780 mm
Width: 570 mm
Height: 680 mm
Dry weight: 94 Kg

Are you looking for a generator with different technical characteristics? [Here](#) you can find the area dedicated to GREENPOWER generators or other specialized brands.

Images and technical data not binding.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	6.6
Continuous power single phase (KW)	6
Maximum power single phase (KVA)	6.6
Continuous power single phase (KVA)	6
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x 230V 32A CEE - 1 x 230V 16A SCHUKO
Engine	Honda GX390
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Elettrico
Engine capacity (cm ³)	389
Number cylinders	1
Cooling	Air
Alternator	LINZ E1C10 MI
Poles	2
Fuel tank capacity (L)	6.1
Consumption (L/h)	2.1 at 75% of the load

Running time (h)	2.95 at 75% of the load
Length (mm)	780
Width (mm)	570
Height (mm)	680
Dry weight (Kg)	94
Silenced	No
Super silenced	No
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	Capacitor / AVR (optional)
Engine manufacturer	Honda