



GENERATOR SINGLEPHASE 3,3KVA 3300I

Reference: 3300I

GENERATOR 3300I SINGLEPHASE 3,3KVA 3KW SILENCED INVERTER

The **Generator SinglePhase 3,3KVA 3KW 3300I Silenced inverter** è powered by a gasoline engine, with engine produced in Italy and guaranteed in every way, the 3300I is ideal for both professional and hobbyist use.

The strengths of the generator 3300I are: the inverter technology that allows to reduce consumption and noise as well as offering a high level of functionality, **lightweight only 30kg**, compactness Length: 560 mm Width: 310 mm Height: 490 mm, ease of use and modern design. The Generator SinglePhase 3,3KVA è equipped with a manual rope start very easy to start and mounts a 4-stroke engine to optimize performance, **consumes only 1.2Lt/h** in small size.

The Generator 3300I SinglePhase 3,3KVA 3KW it's has been specially developed for camping, caravans, houses, and hobby applications, but also for work being very robust and handy, being able to use all its power of with [inverter. technology](#)

The range Generators 3300I inverter

The generator 3300I is a product that respects a high quality standard and guarantees a high level of reliability. For this reason the Generator SinglePhase 3,3KVA is able to ensure 12 months warranty and availability of spare parts all over the world.

The strengths of the generator 3300I are: the high quality, the components, the lightness, the compactness, the ease of use and also the modern design.

This Generator SinglePhase 3,3KVA is specially developed for camping, caravans, home use, hobby, easy to use and reliable.

The advantages of Inverter technology

When the unit is turned on the engine idles, as soon as more electricity is drawn at a certain point, the engine automatically accelerates to cover the required electricity consumption.

This results in a significant reduction in fuel consumption! In addition, all Generator SinglePhase 3,3KVA with inverter technology also have the automatic voltage regulator AVR.

Technical Features of the Generator SinglePhase 3,3KVA 3300I

Maximum Power Single-phase: 3 KW
Maximum Power Single-phase: 3.3 KVA
Fuel: Gasoline
Voltage: 230V

Frequency: 50Hz
Starting system: Recoil
Consumption: 1.2 Lt/h
Length: 560mm
Width: 310mm
Height: 490mm
Weight: 30kg
Super silenced
Inverter

If you want a different generator you can see the following models always of the same [Silenced Inverter Range](#).

Images and technical data not binding.

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	3
Maximum power single phase (KVA)	3.3
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	2 Schuko
Emissions Regulations	Stationary Use
Engine rpm (rpm)	3000
Starting system	Manual recoil
Number cylinders	1
Fuel tank capacity (L)	6.5
Consumption (L/h)	1.2
Running time (h)	5.42
Acoustic pressure	62 dB(A) at 7 m
Length (mm)	560
Width (mm)	310
Height (mm)	490
Dry weight (Kg)	30
Silenced	Yes
Super silenced	Yes
Product type	Generator
ATS Switch device	No ATS
Voltage regulator	Inverter