Man.El.Service Srl
Torino: +39 011 25 35 33 I Milano: +39 02 83 62 30 79
info@manelservice.com
Via Carlo Pittara 46 - 10151 Torino (TO) - Italy
PIVA 09031950018 - Num. REA: 1020262
SDI 5RUO82D Cap. Soc. € 20.000 I.V

Scangrip Connect Power Supply

Reference: 03.6123C

Scangrip Connect Power Supply

UNLIMITED LIGHT AVAILABILITY WITH THE CONNECT WORK LIGHT POWER SUPPLY
The new CONNECT power supply replaces the old power supply that only worked with CAS work lights.

The new CONNECT power supply works with both CONNECT work lights and CAS lights.

Technical Specifications

Cable: 5m / 2x0.75 mm2 H05RN-F
Maximum Power Consumption: 90 W
AC Operating Voltage: 100-240 Vac
Frequency: 50 / 60 Hz
CAS Compatibility: SCANGRIP CONNECT work lights 12V-18V
Length: 124 mm
Width: 83 mm
Height: 72 mm
Net Weight: 1 kg

Looking for a construction light with different technical specifications? HERE you can find the entire range of SCANGRIP construction lights or other brands specialized in the sector.

Images and technical data are not binding and may be subject to revision by the manufacturer.

Technical Sheet

Frequency (Hz)	50 / 60
Voltage (V)	100 - 240
Length (mm)	124
Width (mm)	83
Height (mm)	72
Dry weight (Kg)	1
Power consumption (W)	90