



PRAMAC GBW15Y Generator Set Three-phase ACP 13kVA Enclosure with automatic control panel

Reference: SB130TYAK02

PRAMAC GBW15Y GENERATOR SET ACP THREE-PHASE 13KVA

The PRAMAC GBW15Y three-phase generator delivers 11.4 kW with a diesel engine running at 1500 rpm. The PRAMAC GBW15Y generator is equipped with electric start. The alternator of the PRAMAC GBW15Y generator has brushes with a compound voltage regulator. The Yanmar diesel engine makes the GBW15Y generator highly reliable, as it has been designed and built using top-quality materials.

Thanks to its soundproof canopy, this generator is super-silenced. In addition, it is easy to transport, install, and position thanks to its compact size. This model is ideal for emergency backup, construction, mobile workshops, and industrial applications. The PRAMAC GBW15Y three-phase generator is suitable for outdoor use on construction sites or for small professional jobs.

Technical specifications of the PRAMAC GBW15Y ACP Three-Phase Generator:

Maximum three-phase power: 11.44 kW
Continuous three-phase power: 10.4 kW
Fuel: Diesel
Voltage: 400 V
Frequency: 50 Hz
Engine: Yanmar 3TNV88-BGPGE
Starting system: Electric
Fuel consumption: 3.8 L/h at 100% load
Length: 1645 mm
Width: 870 mm
Height: 1072 mm
Weight: 430 Kg
Compound

ACP Automatic Control Panel:

Integrated panel connected to the generator, with a microprocessor control module that collects all the electronic control, command, and monitoring circuits. Direct switching control terminal block (ACP)
N.1 3P+N+T CEE 400V 32A

The PRAMAC GBW15Y power generator is a professional diesel genset developed by Pramac with the features and equipment required to deliver a superior-class product. With its low noise level, the PRAMAC GBW15Y generator is ideal for use in residential areas or during non-working hours.

The GBW15Y generator is equipped with a reliable diesel engine, premium components, and complete instrumentation.

If you are looking for a generator like the PRAMAC GBW15Y three-phase power generator, we recommend browsing our catalog of [land-based generators](#) to find the one that best suits your needs.

Phase	Three phase
Maximum power three phase (KW)	11.44
Continuous power three phase (KW)	10.4
Maximum power three phase (KVA)	14.3
Continuous power three phase (KVA)	13
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	400
Sockets configuration	1 x 400V 32A 3P+N+T CEE
Engine	Yanmar 3TNV88-BGPGE, naturally aspirated
Emissions Regulations	Stage 5
Engine rpm (rpm)	1500
Speed governor	Mechanical
Starting system	Elettrico
Engine capacity (cm ³)	1642
Number cylinders	3
Cylinders' position	In line
Oil capacity (L)	6.9
Cooling	Water
Alternator	Linz E1S13MD, with brushes
Poles	4
Fuel tank capacity (L)	51
Consumption (L/h)	2.8 at 75% of the load / 3.8 at 100% of the load
Running time (h)	18 at 75% of the load / 13.5 at 100% of the load
Acoustic power	93 dB(A)
Acoustic pressure	64 dB(A) at 7 m
Length (mm)	1645
Width (mm)	870
Height (mm)	1072
Dry weight (Kg)	430
Silenced	Yes
Super silenced	Yes
Product type	Generator
ATS Switch device	Optional ATS
Voltage regulator	Compound

Engine manufacturer

Yanmar