



GENSET MG7.5 H-A Generator 7KVA STAGE V

Reference: MG 7.5 H/A

GENSET MG7.5 H-A GENERATOR 7KVA STAGE V

The GENSET Generator MG7.5 H-A 7KVA Stage V is a high-quality device designed to ensure reliable and durable performance. Equipped with a powerful Honda GX 390 OHV gasoline engine running at 3000 RPM and compliant with Stage V regulations, this model is perfect for a wide range of applications, both professional and domestic.

Technical Specifications of the GENSET MG7.5 H-A 7KVA Stage V Generator:

Maximum Power:

Single-phase: 2.5 KVA / 2 KW

Three-phase: 7 KVA / 5.6 KW

Voltage: 230 V - 400 V

Frequency: 50 Hz

Starting System: Electric

Engine: Honda GX 390 OHV, 390 cm³, 8.2 HP (6.1 kWm), air-cooled

Fuel Tank Capacity: 6.1 liters

Fuel Consumption: 3.3 liters/hour at 75% load

Dimensions: 725 mm (length) x 515 mm (width) x 585 mm (height)

Weight: 95 kg

Features and Benefits

The GENSET MG7.5 H-A Stage V Generator offers numerous features that make it an excellent choice:

Lifting Hook: Integrated into the frame for easy handling and transport.

Automatic Low Oil Shutdown: Protects the engine from potential damage.

GENSET MG7.5 H-A 7KVA Stage V Electrical Outlets:

1 three-phase socket 16 A - 400 V

1 single-phase socket 16 A - 230 V

Integrated Safety Features: Differential thermal switch, power output protections, and voltmeter.

Connectivity: Connector for AMF-ATS panel and/or remote control.

Automatic Voltage Regulator (AVR): Maintains stable voltage to protect connected devices.

Protection Rating: IP23, offering a good level of protection against dust and water splashes.

The GENSET MG7.5 H-A Stage V is designed to operate in challenging environmental conditions, with an ambient temperature up

to 40 degrees and altitudes up to 1000 meters. The sound power level is 99 dB (74 dB at 7 meters), ensuring relatively quiet operation for a GENSET MG7.5 H-A generator of this power.

The GENSET MG7.5 H-A 7KVA Stage V represents the ideal solution for those seeking a reliable, powerful, and versatile generator. With the Honda GX 390 OHV engine and automatic starting capability, this generator offers excellent performance in a compact and robust design. For both professional and domestic applications, the GENSET MG7.5 H-A 7KVA Stage V Generator is the perfect choice to ensure a constant and secure power source.

Looking for a generator with different features? [HERE](#) you can find the full range of GENSET products or other specialized brands in the industry.

Images and technical data are not binding and may be subject to revisions by the supplier.

Technical Sheet

Phase	Single phase / Three phase
Maximum power single phase (KW)	2.5
Maximum power single phase (KVA)	2
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	1 x 400V 16A CEE - 1 x 230V 16A CEE
Engine	Honda GX390, 4 stroke, OHV
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Electric
Engine capacity (cm ³)	390
Number cylinders	1
Cooling	Air
Alternator	Synchronous
Protection degree	IP23
Motor insulation class	H
Fuel tank capacity (L)	6.1
Consumption (L/h)	3.3 at 75% of the load
Acoustic power	100 dB(A)
Acoustic pressure	74 dB(A) at 7 m
Length (mm)	725
Width (mm)	515
Height (mm)	585
Dry weight (Kg)	95

Silenced	No
Super silenced	No
ATS Switch device	Optional ATS
Voltage regulator	AVR
Engine manufacturer	Honda
