



## FISCHER PANDA 30x Marine Generator PMS Three-Phase 30kVA 25.5 kW

Reference: 0004787-3PH

### FISCHER PANDA 30x SUPER-SILENT THREE-PHASE MARINE GENERATOR 30 KVA

Fischer Panda 30x 30 KVA three-phase marine generator with a 3000 rpm motor. The Fischer Panda 30x marine generator is designed with a soundproof cabin for super-silent operation. The Fischer Panda 30x marine generator is powered by a Kubota diesel engine. The alternator of the Fischer Panda 30x marine generator is a 2-pole one with insulation class H. With its compact dimensions and low weight, the Fischer Panda 30x marine generator is also suitable for installation on small boats.

#### Main Features FISCHER PANDA 30x:

##### High Power:

It delivers a maximum power of 25.5 kW and a continuous power of 22.9 kW.

The maximum power of 30 kVA and the continuous power of 27 kVA make it suitable for heavy loads. heavy duty.

##### Reliable Engine:

Equipped with a 4-cylinder Kubota V1505T engine, known for its robustness and durability.

The 1498 cm<sup>3</sup> diesel engine ensures efficient and reliable operation.

##### Stable Performance:

The 50 Hz frequency and 400 V voltage ensure a constant power supply.

The voltage regulator with x/fp control maintains stable voltage even under variable loads.

##### Quiet Operation:

Whether silenced or super silenced, this generator is designed to minimize noise.

##### Robust Construction:

With a total dry weight of 403 kg, this generator is built to last.

Fischer's compact dimensions (1010 x 515 x 674 mm) make installation and transportation easy.

FISCHER PANDA 30x Technical Specifications:

Phase type: three-phase

Maximum three-phase power (KW): 25.5

Continuous three-phase power (KW): 22.9

Maximum three-phase power (KVA): 30

Continuous three-phase power (KVA): 27

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 400

Engine: Kubota V1505T

Engine speed (rpm): 3000

Starting: Electric

Displacement (cm<sup>3</sup>): 1498

Number of cylinders: 4

Number of poles: 2

Length (mm): 1010

Width (mm): 515

Height (mm): 674

Silent: Yes

Super Silenced: Yes

Engine insulation class: H

Product type: Generator

Voltage regulator: x/fp control

Engine brand: Kubota

Weight (Kg): 403

If you are looking for a marine generator like the Fischer Panda 30x but with different technical features, you can browse the entire catalog of [marine generators](#).

Images and technical data are not binding. Please always consult the technical data sheet issued by the manufacturer. Manel Service assumes no responsibility for any changes made by the manufacturer.

## Technical Sheet

Phase	Three phase
Maximum power single phase (KW)	25.5
Continuous power single phase (KW)	22.9
Maximum power single phase (KVA)	30
Continuous power single phase (KVA)	27
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	400
Engine	Kubota V1505T
Engine rpm (rpm)	3000
Starting system	Elettrico
Engine capacity (cm <sup>3</sup> )	1498
Number cylinders	4
Poles	2
Motor insulation class	H
Length (mm)	1010
Width (mm)	515
Height (mm)	674
Dry weight (Kg)	355
Silenced	Yes
Super silenced	Yes
Product type	Generator
Voltage regulator	Control x/fpControl
Engine manufacturer	Kubota
Weight (Kg)	403