



PRAMAC GPW60P/FNE Generator Set 66.3 KVA Silenced

Reference: BP600TPA013

PRAMAC GPW60P/FNE 66.3 KVA Silent Generator

The PRAMAC GPW60P/FNE 66.3 KVA Silent Generator is the ideal solution for those seeking a powerful, efficient, and quiet generator, perfect for industrial or residential applications. Thanks to its compact design and advanced technical specifications, it offers reliable performance even in the most demanding conditions.

The PRAMAC GPW60P/FNE generator set is three-phase with a maximum power of 66.3 KVA and is designed with a Perkins 1103A-33TG2 diesel engine.

Thanks to its canopy, this generator set is super-silenced and very robust.

Technical characteristics of the PRAMAC GPW60P/FNE

Phase type: Three-phase
Continuous power: 60.1 KVA / 48.1 KW
Maximum power: 66.3 KVA / 53 KW
Engine: Perkins 1103A-33TG2
Emissions standard: Not Emitted
Engine speed: 1500 rpm
Starting: Electric
Fuel: Diesel
Voltage: 230 / 400 V
Frequency: 50 Hz
Tank capacity: 80 L
Consumption at 75% load: 10.33 l/h
Autonomy at 75% load: 7.7 h
Sound pressure: 63 dB(A) @ 7 m
Length: 2200 mm
Width: 1020 mm
Height: 1904 mm
Dry weight: 1228 kg

Looking for a generator with different technical specifications? Check out the [dedicated section](#) for PRAMAC generators or other specialized brands.

Images and technical data are not binding.

Technical Sheet

Phase

Three phase

Maximum power three phase (KW)	53
Continuous power three phase (KW)	48.1
Maximum power three phase (KVA)	66.3
Continuous power three phase (KVA)	60.1
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	230 / 400
Emissions Regulations	NON EMISSIONATO
Engine rpm (rpm)	1500
Speed governor	Mechanical
Starting system	Elettrico
Engine capacity (cm ³)	3300
Number cylinders	3
Cylinders' position	In line
Cooling	Water
Alternator	Mecc Alte ECP32-2M4 C
Poles	4
Fuel tank capacity (L)	80
Consumption (L/h)	10.33 at 75% of the load
Running time (h)	7.7 at 75% of the load
Acoustic pressure	63 dB(A) a 7 m
Width (mm)	1020
Height (mm)	1904
Dry weight (Kg)	1228
Silenced	Yes
Engine manufacturer	Perkins