



WFM SE12000-MTHE AVR

Reference: 06009

Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	5.6
Maximum power single phase (KVA)	7
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x 230V 16A - 1 x 230V 16A CEE
Engine	Honda GX390
Engine rpm (rpm)	3000
Starting system	Electric
Engine capacity (cm ³)	389
Number cylinders	1
Oil capacity (L)	1.1
Cooling	Air
Fuel tank capacity (L)	6.5
Consumption (L/h)	3.1 at 100% of the load
Running time (h)	2.09 at 100% of the load
Acoustic power	96 dB(A)
Acoustic pressure	71 dB(A) at 7 m
Length (mm)	780
Width (mm)	520

Height (mm)	560
Dry weight (Kg)	81
Silenced	No
Super silenced	No
ATS Switch device	No ATS
Voltage regulator	No
Engine manufacturer	Honda
