



## WFM SE12000-MTHE AVR

Reference: 06034

### Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	3.6
Maximum power single phase (KVA)	4.5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x 230V 16A - 1 x 230V 16A CEE
Engine	Honda GX270
Engine rpm (rpm)	3000
Ignition	Recoil
Starting system	Pull starter
Engine capacity (cm <sup>3</sup> )	270
Number cylinders	1
Oil capacity (L)	1.1
Cooling	Air
Fuel tank capacity (L)	20
Consumption (L/h)	2.4 at 100% of the load
Running time (h)	8.33 at 100% of the load
Acoustic power	95 dB(A)
Acoustic pressure	70 dB(A) at 7 m
Length (mm)	750

---

Width (mm)	560
Height (mm)	620
Dry weight (Kg)	75
Silenced	No
Super silenced	No
ATS Switch device	No ATS
Voltage regulator	No
Engine manufacturer	Honda

---