



GENSET MGF 33 Y - SINGLE-PHASE/THREE-PHASE GENERATOR 33 KVA AVR

Reference: MGF 33 Y

GENSET MGF 33 Y

The GENSET MGF 33 Y is a single-phase/three-phase 33 KVA diesel generator with electric start and AVR voltage regulator. Thanks to its compact size and its very low weight, the GENSET MGF 33 Y is a light and easy to transport generator. The GENSET MGF 33 Y also has a low fuel consumption: only 6.4 Lt/h at 75% of the load. The GENSET MGF 33 Y generator set, thanks to the high quality and efficiency of its components, is ideal for various types of work: from small hobby jobs to large construction sites.

Images and technical data are not binding.

Technical Sheet

Phase	Three phase
Maximum power three phase (KVA)	33
Continuous power three phase (KVA)	30
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	400
Sockets configuration	
Engine	Yanmar 4TNV98, 4 stroke
Emissions Regulations	Stationary Use
Engine rpm (rpm)	1500
Starting system	Electric
Engine capacity (cm ³)	3319
Number cylinders	4
Cooling	Water
Protection degree	IP23
Motor insulation class	H

Fuel tank capacity (L)	40
Consumption (L/h)	6.4
Running time (h)	6.25
Acoustic power	97 dB(A)
Acoustic pressure	72 dB(A) at 7 m
Length (mm)	1640
Width (mm)	770
Height (mm)	1076
Dry weight (Kg)	830
Silenced	Yes
Super silenced	Yes
Product type	Generator
ATS Switch device	Optional ATS
Voltage regulator	AVR
Engine manufacturer	Yanmar