



## TECNOGEN H8000LX Generator Set Single-phase 7.2KVA

Reference: H 8000 LX - C

### TECNOGEN H8000LX GENERATOR SET SINGLE-PHASE 7.2KVA

The TECNOGEN H8000LX Generator Set Single-Phase 7.2KVA is equipped with a Honda gasoline engine running at 3000 RPM. The TECNOGEN H8000LX generator is easy to use, compact, handy, and easy to maintain. The TECNOGEN H8000LX 7.2KVA single-phase generator features a manual start. This generator is perfect for both hobby and professional use, thanks to the reliability and efficiency of the Honda gasoline engine and the high-quality components it is built with.

#### Technical Features of the TECNOGEN H8000LX Generator Set Single-Phase 7.2KVA:

Maximum Single-Phase Power: 5.8 KW  
Maximum Single-Phase Power: 7.2 KVA  
Fuel: Gasoline  
Voltage: 230 V  
Frequency: 50 Hz  
Engine: Honda GX390  
Starting System: Manual  
Length: 750 mm  
Width: 560 mm  
Height: 620 mm  
Weight: 88 Kg

#### Why buy the TECNOGEN H8000LX Generator Set Single-Phase 7.2KVA?

It primarily solves power outage problems in various environments, from homes to businesses. The TECNOGEN H8000LX generator is also used to supply power at construction sites and for hobby use. Professional generators are lightweight, easy to transport, compact, and robust, simple to use, and have low operating costs. Additionally, they offer excellent value for money.

The TECNOGEN H8000LX can be equipped with lifting hooks, making it convenient to move the power generator with an overhead crane or a small hoist.

#### The Complete TECNOGEN Range:

TECNOGEN generators are available in both single-phase and three-phase versions, with power outputs ranging from 2.3 to 21 KVA MAX. They are equipped with gasoline or diesel engines, air-cooled, running at 3000 RPM, and featuring electric and/or manual recoil start. Compact, simplified, and economical, they offer an excellent price/performance/size/weight ratio. Easily transportable due to their compact design, they are ideal for those who need an affordable energy source while still benefiting from top-quality components ensuring absolute reliability. The gasoline-powered TECNOGEN models from the COMPACT line, thanks to the latest-generation Honda engines, comply with the noise directive 2000/14/EC.

Looking for a different model of the TECNOGEN H8000LX Single-Phase Generator 7.2KVA? Visit the dedicated section for [land-based generators](#).

Images and technical data are for reference only.

## Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	5.8
Maximum power single phase (KVA)	7.2
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Engine	Honda GX390
Emissions Regulations	Stage 5
Engine rpm (rpm)	3000
Starting system	Manuale
Engine capacity (cm <sup>3</sup> )	389
Number cylinders	1
Cooling	Air
Fuel tank capacity (L)	20
Consumption (L/h)	1.9
Running time (h)	10.5
Acoustic power	96 dB(A)
Length (mm)	750
Width (mm)	560
Height (mm)	620
Dry weight (Kg)	88
Silenced	No
Super silenced	No
ATS Switch device	No ATS
Voltage regulator	No
Engine manufacturer	Honda