



GREEN POWER GP16SH-PW-C SOUNDPROOF

Reference: 00371-OBM

The GREEN POWER 1500 rpm generators are designed for versatile use, from construction sites to industry, from agriculture to civil protection.

Robust welded steel frames with built-in tank of variable capacity produced by Green Power, engines and alternators supplied by the most important manufacturers in the sector and cutting-edge control units are the elements to ensure generators of excellent quality.

The hoods are made of steel, which allows them to be used in tropical environments. The Green Power covers guarantee maximum accessibility for maintenance and cleaning operations.

Green Power's strong point is the design and implementation within the company, a feature that helps to reduce the time to market of the product and allows any customization.

You can choose from several versions:

- Silenced group with Compound-Linz alternator (automatic control pack)
- Silenced group with AVR-Leroy alternator (automatic control pack)
- Silenced group with high AVR-Mecc alternator (automatic control unit)
- Silenced group with AVR-Stamford alternator (automatic control unit)

The image is purely indicative.

Technical Sheet

Phase	Three phase
Maximum power three phase (KW)	11.6
Continuous power three phase (KW)	10.5
Maximum power three phase (KVA)	14.5
Continuous power three phase (KVA)	13.1
Fuel	Diesel
Frequency (Hz)	50
Voltage (V)	230 / 400
Sockets configuration	Presse 32A 5P

Engine	PERKINS 403A-15G1, 4 stroke naturally aspirated
Emissions Regulations	Non Emissionati
Engine rpm (rpm)	1500
Speed governor	Mechanical
Starting system	Elettrico
Engine capacity (cm ³)	1496
Number cylinders	3
Cylinders' position	In line
Cooling	Water
Alternator	Linz E1S13ME/4, synchronous, with brushes
Poles	4
Fuel tank capacity (L)	70
Consumption (L/h)	2.8 al 75% del carico
Running time (h)	25 at 75% load
Acoustic pressure	70 dB(A) at 7 m
Length (mm)	1750
Width (mm)	700
Height (mm)	1020
Dry weight (Kg)	560
Silenced	Yes
Super silenced	No
ATS Switch device	Optional ATS
Voltage regulator	Compound / AVR (optional)