



## TECNOGEN H5000SS/A GENERATOR WITH SEPARATE AUTOMATIC PANEL

Reference: H5000SS/A - C

### TECNOGEN H5000SS/A 3,6 KW GENERATOR WITH AUTOMATIC PANEL

Generator TECNOGEN H5000SS/A single-phase power of 3,6 KW with Honda engine of 3000 rpm supplied by gasoline. The TECNOGEN H5000SS/A generating set is easy to use and is small in size, easy to handle and easy to maintain. The TECNOGEN H5000SS/A generating set is equipped with electric start. This generator set is perfect for both hobby and professional use, thanks to the reliable gasoline-powered Honda engine and all the high quality components it is composed of.

**Pre-equipped with automatic panel supplied separately for automatic start in case of power failure.**

#### Why buy a H5000SS/A genset?

First of all, they solve problems of power failure during blackouts in various environments, from homes to businesses. The TECNOGEN H5000SS/A genset is also used to provide electricity on construction sites and for hobby use.

The TECNOGEN H5000SS/A genset can be fitted with lifting hooks, which are very convenient for moving the power generator with an overhead crane or a small crane.

#### The following are the main features:

Maximum single-phase power: 3.6 KW  
Maximum single-phase power: 4.5 KVA  
Fuel: Gasoline  
Voltage: 230 V  
Frequency: 50 Hz  
Motor: HONDA GX270  
Starting: Automatic  
Length: 940 mm  
Width: 510 mm  
Height: 550 mm  
Weight: 106 Kg  
With ATS automatic panel

#### All TECNOGEN range

The TECNOGEN units are available in both single-phase and three-phase versions, with powers from 2.3 to 21 KVA MAX, equipped with gasoline or diesel engines, air-cooled, 3000 rpm, with electric and/or manual start with recoil starter. Compact, simplified and economical, they boast an excellent price/performance/size/weight ratio. Easily transportable thanks to the reduced dimensions due to an essential equipment, are indicated to all those who need an economic source of energy, however, assembled with a first-class components that ensure absolute reliability.

Are you looking for a different model of current generator or generator set? Visit the section dedicated to [land based generator sets](#).

Images and technical data not binding.

## Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	3.6
Maximum power single phase (KVA)	4.5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Engine	HONDA GC160
Engine rpm (rpm)	3000
Starting system	Electric
Engine capacity (cm <sup>3</sup> )	270
Number cylinders	1
Cooling	Air
Fuel tank capacity (L)	7
Consumption (L/h)	1.5
Running time (h)	4.6
Acoustic power	88 dB(A)
Length (mm)	940
Width (mm)	510
Height (mm)	550
Dry weight (Kg)	106
Silenced	No
Super silenced	Yes
ATS Switch device	ATS Included
Voltage regulator	Capacitor / AVR (optional)
Engine manufacturer	Honda