



## VINCO AG-HA-6500

Reference: 80554

### Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	4.2
Continuous power single phase (KW)	4
Maximum power single phase (KVA)	5.25
Continuous power single phase (KVA)	5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	3 x 230V
Engine	CP188F, 4 stroke
Engine rpm (rpm)	3000
Starting system	Electric
Engine capacity (cm <sup>3</sup> )	389
Number cylinders	1
Oil capacity (L)	1.1
Cooling	Air
Alternator	Synchronous
Fuel tank capacity (L)	25
Consumption (L/h)	2.31
Running time (h)	10.1
Acoustic power	97 dB(A) a 4 m

---

Length (mm)	730
Width (mm)	590
Height (mm)	595
Dry weight (Kg)	78
Inverter	No
AVR	Yes
Compound	No
Silenced	No
Super silenced	No

---