



## WFM SE12000-MTHE AVR

Reference: 04040 / 09064

### Technical Sheet

Phase	Single phase
Maximum power single phase (KW)	3.6
Maximum power single phase (KVA)	4.5
Fuel	Natural Gas
Frequency (Hz)	50
Voltage (V)	230
Sockets configuration	1 x 230V 16A 3P CEE
Engine	Honda GX270, OHV
Engine rpm (rpm)	3000
Starting system	Electric
Engine capacity (cm <sup>3</sup> )	270
Number cylinders	1
Oil capacity (L)	1.1
Cooling	Air
Natural Gas consumption (m <sup>3</sup> /h)	2.9 at 100% of the load
Fuel tank capacity (L)	7
Acoustic power	88 dB(A)
Acoustic pressure	63 dB(A) at 7 m
Length (mm)	1000
Width (mm)	515
Height (mm)	595

---

Dry weight (Kg)	106
Silenced	Yes
Super silenced	Yes
ATS Switch device	Optional ATS
Voltage regulator	AVR
Engine manufacturer	Honda

---