



SINCRO FK2 LC Steel Single Phase Synchronous AC Alternator 18.5 kVA Capacitor

Reference: FK2 LC Steel j609b C25.4

SINCRO FK2 LC ALTERNATOR 22,0 KVA SINGLE-PHASE

Alternator SINCRO FK2 LC single phase with a power of 22.0KVA, this unit has a Brushless operation equipped with capacitor voltage regulator.

The alternator is designed for operation at frequency 50 or 60 HZ, the possibility of working on these two frequencies makes it possible the application for any service voltage increasing its versatility, for the correct operation. SINCRO FK2 LC has been realized with the body entirely in steel, this makes the alternator very resistant and suitable for heavy duty use.

All the components that make up the SINCRO FK2 LC alternator are subjected to a specific coating and/or impregnation process to safeguard the generator's functionality and protect the critical parts under various conditions of use.

SINCRO FK2 LC is a brushless alternator, this feature together with the high efficiency of the regulator ensure a low level of interference with radio waves.

SINCRO alternators are all equipped with a voltage regulator, in the case of the FK2 LC model with a capacitor.

Select the alternator that meets the **technical specifications you require**, visit our [dedicated section](#) to find out how.

TECHNICAL FEATURES SINCRO FK2 LC

Phase Type: Single-phase
Maximum singlephase output: 17.6 KW
Maximum singlephase continuous output: 14.4 KW
Maximum singlephase output: 22.0 KVA
Maximum singlephase continuous output: 18.5 KVA
Frequency: 50-60 Hz
Voltage: 230 V
Protection rating: IP23
Agent speed: 3000 rpm
Number of poles: 2
Weight: 96Kg
Brushless
Voltage regulator: Condenser
Type of alternator: constant speed

Looking for a product with different features? [Here](#) you can find the full range SINCRO and other specialized brands.

Images and technical data are not binding and subject to changes by the manufacturer

Technical Sheet

Phase	Single phase
Frequency (Hz)	50
Voltage (V)	230
Engine rpm (rpm)	3000
Poles	2
Single-phase power (KW)	18.5
Single-phase power (KVA)	18.5
Efficiency (%)	84
Protection degree	IP23
Dry weight (Kg)	96
Brushes	No
Type of alternator	Constant Speed
Voltage regulator	Capacitor