



SINCRO ET2 LBF Single / Three Phase Synchronous AC Alternator 10 kVA Compound

Reference: ET2 LBF

Three phase brushes alternator - Compound.

- Self-regulated
- IP23
- Standard voltage 230/400 V - 50 Hz
- Short circuit current greater than 3 In
- Standard coupling IM B35 cone 22.14 / cone 25.4 / cone 35
- Couplings IM B34, IM B35, SAE
- With reinforced phase

The image is purely indicative.

Technical Sheet

Phase	Single phase / Three phase
Frequency (Hz)	50
Voltage (V)	230 / 400
Engine rpm (rpm)	3000
Poles	2
Single-phase power (KW)	4.8
Single-phase power (KVA)	6
Three-phase power (KW)	8
Three-phase power (KVA)	10
Efficiency (%)	85
Protection degree	IP23
Dry weight (Kg)	41.2
Brushes	Yes
Type of alternator	Constant Speed
Voltage regulator	Compound