



SINCRO FK4 MBS Single Phase Synchronous AC Alternator 5.5 kVA Capacitor

Reference: FK4 MBS

Single phase brushless alternator - Capacitor.

- Self-regulated
- IP23
- Standard voltage 230 V - 50 Hz
- Short circuit current greater than 3 In
- Standard coupling IM B35 cone 25.4 / cone 35
- Couplings IM B34, IM B35, SAE

The image is purely indicative.

Technical Sheet

Phase	Single phase
Frequency (Hz)	50
Voltage (V)	230
Engine rpm (rpm)	1500
Poles	4
Single-phase power (KW)	5.5
Single-phase power (KVA)	5.5
Efficiency (%)	77
Protection degree	IP23
Dry weight (Kg)	36
Brushes	No
Type of alternator	Constant Speed
Voltage regulator	Capacitor