



LINZ SP10S C 2.6 kVA 50 Hz Single-phase Brushless Alternator with Capacitor

Reference: SP10S C 50 Hz

The SP series consists of single-phase, brushless, 2-pole alternators with auxiliary winding (charged on the condenser) that ensures voltage regulation.

CHARACTERISTICS

Compact and easy to assemble
Possibility of vertical mounting
Rear or top accessory panel
High efficiency
Gamma: Single-phase alternators
Poles: 2
Phases: Single-phase
Adjustment: CONDENSER

Technical Sheet

| | |
|-------------------------------------|------------------------|
| Phase | Single phase |
| Continuous power single phase (KW) | 2.6 |
| Continuous power single phase (KVA) | 2.6 |
| Frequency (Hz) | 50 |
| Voltage (V) | 230 |
| Engine rpm (rpm) | 3000 |
| Alternator | Synchronous, brushless |
| Poles | 2 |
| Single-phase power (KW) | 1.7 |
| Single-phase power (KVA) | 2.6 |
| Protection degree | IP21 |
| Motor insulation class | H |
| Length (mm) | 275 |
| Width (mm) | 200 |

| | |
|--------------------|----------------|
| Height (mm) | 200 |
| Brushes | No |
| Type of alternator | Constant Speed |
| Voltage regulator | Capacitor |
| Weight (Kg) | 15 |
