



## LINZ E1E10L L Singlephase alternator 115V/230V 8 kVA 50 Hz AVR

## **Product description:**

The **SPE** and **E1E** series consist of single-phase 2-pole alternators with brushes and AVR electronic regulation.

## **CHARACTERISTICS**

- Compact and easy to assemble
- High voltage accuracy
- Wide range of accessories
- AVR with built-in protections
- Range: Single-phase alternators
- Poles: 2
- Phases: Single-phase
- Adjustment: AVR
- Application: PORTABLE

Images and technical data are not binding.

## **Product features:**

Phase: Single phase

Continuous power single phase (KW): 8 Continuous power single phase (KVA): 8

Frequency (Hz): 50 Voltage (V): 115 / 230 Engine rpm (rpm): 3000

Alternator: Synchronous, brushless





Poles: 2

Single-phase power (KVA): 8

Protection degree: IP21 Motor insulation class: H

Length (mm): 395 Width (mm): 195 Height (mm): 297 Brushes: Yes

Type of alternator: Constant Speed

Voltage regulator: AVR

Weight (Kg): 37.8

