

## LINZ E1S10M H Threephase alternator 230/400V 7 kVA 50 Hz Compound

## **Product description:**

Ø.

E1S/2 series are three-phase 2 poles alternators with brushes and compound regulation..

## **CHARACTERISTICS**

- Possibility to feed any type of load
- · Compact and easy to assemble
- High starting capacity
- High efficiency
- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: COMPOUND
- Application: PORTABLE

## **Product features:**

Phase: Three phase Continuous power three phase (KW): 5.6 Continuous power three phase (KVA): 7 Frequency (Hz): 50 Voltage (V): 230 / 400 Engine rpm (rpm): 3000 Alternator: Synchronous

PrestaShop

R)

Poles: 2 Single-phase power (KVA): 7 Protection degree: IP21 Motor insulation class: H Length (mm): 294 Width (mm): 195 Height (mm): 295 Brushes: Yes Type of alternator: Constant Speed Voltage regulator: Compound Weight (Kg): 33.1

R