



GREEN POWER GP66S/K-N SOUNDPROOF (MANUAL CONTROL UNIT)

Product price:

13.299,00 € tax excluded

Product description:

The GREEN POWER 1500 rpm generators are designed for versatile use, from construction sites to industry, from agriculture to civil protection.

Robust welded steel frames with built-in tank of variable capacity produced by Green Power, engines and alternators supplied by the most important manufacturers in the sector and cutting-edge control units are the elements to ensure generators of excellent quality.

The hoods are made of steel, which allows them to be used in tropical environments. The Green Power covers guarantee maximum accessibility for maintenance and cleaning operations.

Green Power's strong point is the design and implementation within the company, a feature that helps to reduce the time to market of the product and allows any customization.

THIS PRODUCT IS ONLY AVAILABLE IN THE AUTOMATIC CONTROL UNIT VERSION

You can choose from several versions:

- -Silenced group with AVR-Leroy alternator (automatic power pack)
- -Silenced group with high AVR-Mecc alternator (automatic control unit)
- -Silenced group with AVR-Stamford alternator (automatic control unit)

The image is purely indicative.





Product features:

Phase: Three phase

Maximum power three phase (KW): 53 Continuous power three phase (KW): 49.6 Maximum power three phase (KVA): 68 Continuous power three phase (KVA): 62

Fuel: Diesel

Frequency (Hz): 50 Voltage (V): 230 / 400

Engine: Kohler KDI3404TM

Emissions Regulations: Non Emissionati

Engine rpm (rpm): 1500 Speed governor: Mechanical Starting system: Elettrico Engine capacity (cm³): 3359

Number cylinders: 4 Cylinders' position: In line

Cooling: Water

Alternator: LINZ PRO 18LF/4 - Sincrono

Poles: 4

Fuel tank capacity (L): 100

Consumption (L/h): 11.3 al 75% del carico Running time (h): 9.62 h al 75% del carico

Length (mm): 2260 Width (mm): 1000 Height (mm): 1400 Dry weight (Kg): 1220

Silenced: Yes

Super silenced: Yes

ATS Switch device: Optional

Voltage regulator: AVR