



# LINZ E1S13S C/2 Three-phase alternator 230V/400V 16 kVA 50 Hz Compound

## Product description:

**E1S/2** series are three-phase 2 poles alternators with brushes and compound regulation..

## CHARACTERISTICS

- Possibility to feed any type of load
- Compact and easy to assemble
- High starting capacity
- High efficiency
- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: COMPOUND
- Application: PORTABLE

## Product features:

Phase: Three phase

Continuous power three phase (KW): 12.8

Continuous power three phase (KVA): 16

Frequency (Hz): 50

Voltage (V): 230 / 400

Engine rpm (rpm): 3000

Alternator: Synchronous



Poles: 2

Three-phase power (KVA): 16

Protection degree: IP21

Motor insulation class: H

Length (mm): 405

Width (mm): 270

Height (mm): 379

Brushes: Yes

Type of alternator: Constant Speed

Voltage regulator: Compound

Weight (Kg): 61