



LINZ E1S13M E/2 Three-phase alternator 277V/480V 32.4 kVA 60 Hz Compound

Product description:

E1S/2 series are three-phase 2 poles alternators with brushes and compound regulation..

CHARACTERISTICS

- Possibility to feed any type of load
- Compact and easy to assemble
- High starting capacity
- High efficiency
- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: COMPOUND
- Application: PORTABLE

Product features:

Phase: Three phase

Continuous power three phase (KW): 25.92

Continuous power three phase (KVA): 32.4

Frequency (Hz): 60

Voltage (V): 277 / 480

Engine rpm (rpm): 3600





Alternator: Synchronous

Poles: 2

Three-phase power (KVA): 32.4

Protection degree: IP21

Motor insulation class: H

Length (mm): 495

Width (mm): 270

Height (mm): 379

Brushes: Yes

Type of alternator: Constant Speed

Voltage regulator: Compound

Weight (Kg): 88

