



# GREEN POWER GP350A/V OPEN (MANUAL CONTROL UNIT)

# **Product price:**

33.595,00 € tax excluded

# **Product description:**

The GREEN POWER 1500 rpm generators are designed for versatile use, from construction sites to industry, from agriculture to civil protection.

Robust welded steel frames with built-in tank of variable capacity produced by Green Power, engines and alternators supplied by the most important manufacturers in the sector and cutting-edge control units are the elements to ensure generators of excellent quality.

The hoods are made of steel, which allows them to be used in tropical environments. The Green Power covers guarantee maximum accessibility for maintenance and cleaning operations.

Green Power's strong point is the design and implementation within the company, a feature that helps to reduce the time to market of the product and allows any customization.

# THIS PRODUCT IS ONLY AVAILABLE IN THE AUTOMATIC CONTROL UNIT VERSION

### You can choose between the versions:

- -Open group with AVR-Leroy alternator (automatic power pack)
- -Open group with AVR-Mecc Alte alternator (automatic power pack)
- -Open genset with AVR-Stamford alternator (automatic power pack)

The image is purely indicative.





## **Product features:**

Phase: Three phase

Maximum power three phase (KW): 276.8 Continuous power three phase (KW): 252 Maximum power three phase (KVA): 346 Continuous power three phase (KVA): 315

Fuel: Diesel

Frequency (Hz): 50 Voltage (V): 230 / 400

Engine: VOLVOTAD1341GE Emissions Regulations: Stage 2

Engine rpm (rpm): 1500 Speed governor: Electronic Starting system: Elettrico Engine capacity (cm³): 12780

Number cylinders: 6 Cylinders' position: In line

Cooling: Water

Alternator: LINZ PRO 22SD/4 - Sincrono

Poles: 4

Fuel tank capacity (L): 188

Consumption (L/h): 48 Lt/h al 75% del carico Running time (h): 9.62 h al 75% del carico

Length (mm): 3200 Width (mm): 1100 Height (mm): 1900 Dry weight (Kg): 2820

Silenced: No

Super silenced: No

ATS Switch device: Optional

Voltage regulator: AVR