



LINZ E1X13M E/2 Three-phase alternator 230V/400V 22 kVA 50 Hz AVR

Product description:

E1X/2 series are three-phase brushless 2 poles alternators with exciter and electronic regulation (AVR).

CHARACTERISTICS

- Compact and mechanically resistant
- Minimum maintenance
- High efficiency
- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: AVR
- Application: PORTABLE, TELECOMMUNICATION

Product features:

Phase: Three phase

Continuous power three phase (KW): 17.6

Continuous power three phase (KVA): 22

Frequency (Hz): 50

Voltage (V): 230 / 400

Engine rpm (rpm): 3000





Alternator: Synchronous

Poles: 2

Three-phase power (KVA): 22

Protection degree: IP21

Motor insulation class: H

Length (mm): 554

Width (mm): 270

Height (mm): 375

Brushes: No

Type of alternator: Constant Speed

Voltage regulator: AVR

Weight (Kg): 97

